

GENERATOR

SDG60S-3B1

| | |
|--------------------------------------|--|
| BRAND | AIRMAN |
| MODEL | SDG60S-3B1 |
| GENERATOR | |
| Type | Dual Voltage |
| Frequency (Hz) | 50 / 60 |
| 3-phase 4 wires | |
| - Prime Output (kVA) | 50 / 60 |
| - Stanby Output (kVA) | 55 / 66 |
| - Voltage (V) | 200/400 / 220/440 |
| - Current (A) | 144/72.2 / 157/78.7 |
| Single-phase auxiliary output | |
| - Voltage (V) | 100 / 110 |
| - Dedicated terminals (kVA) | 7.5×2 / 8.25×2 |
| - Outlets (kVA) | 1.5×4 / 1.65×4 |
| Power factor (%) | 3-phase 80 (lagging) / Single-phase 100 |

| | |
|------------------------------------|--|
| ENGINE | |
| Make, Model | ISUZU BJ-4JJ1X |
| Type | Direct-Injection, Turbo-Charged, Intercooled |
| Rated output (kW) | 51.6 / 61 |
| Rated output (PS) | 70.2 / 82.9 |
| Rated speed (min-1) | 1,500 / 1,800 |
| Fuel tank capacity (L) | 125 |
| Engine oil amount (L) | 15 |
| Battery × quantity | 95D31R×1 |
| DIMENSION & WEIGHT, etc | |
| L×W×H (mm) | 2,080×1,000×1,220 |
| Dry weight (kg) | 1,110 |
| Operating weight (kg) | 1,240 |
| Sound power level in decibels (dB) | 87 / 90 |
| Sound pressure level (dB[A]) | 58 / 62 |
| Designated emissions regulation | JPN Stage 3 |

