

GENERATOR

SDG125S-3A6

BRAND	AIRMAN
MODEL	SDG125S-3A6
GENERATOR	
Type	Dual Voltage
Frequency (Hz)	50 / 60
3-phase 4 wires	
- Prime Output (kVA)	100 / 125
- Stanby Output (kVA)	110 / 137.5
- Voltage (V)	200/400 / 220/440
- Current (A)	289/144 / 328/164
Single-phase auxiliary output	
- Voltage (V)	100 / 110
- Dedicated terminals (kVA)	10×2 / 11×2
- Outlets (kVA)	1.5×2 / 1.65×2
Power factor (%)	3-phase 80 (lagging) / Single-phase 100

ENGINE	
Make, Model	HINO J08C-UP
Type	Direct-Injection, Turbo-Charged
Rated output (kW)	96.3 / 113.6
Rated output (PS)	131 / 153
Rated speed (min-1)	1,500 / 1,800
Fuel tank capacity (L)	250
Engine oil amount (L)	24.5
Battery × quantity	95D31R×2
DIMENSION & WEIGHT, etc	
L×W×H (mm)	2,990×1,180×1,480
Dry weight (kg)	2,050
Operating weight (kg)	2,300
Sound power level in decibels (dB)	90 / 92
Sound pressure level (dB[A])	63 / 64
Designated emissions regulation	JPN Stage 2

