

GENERATOR

SDG25S-3B1

BRAND	AIRMAN
MODEL	SDG25S-3B1
GENERATOR	
Type	Dual Voltage
Frequency (Hz)	50 / 60
3-phase 4 wires	
- Prime Output (kVA)	20 / 25
- Stanby Output (kVA)	22 / 27.5
- Voltage (V)	200/400 / 220/440
- Current (A)	57.5/28.9 / 65.6/32.8
Single-phase auxiliary output	
- Voltage (V)	100 / 110
- Dedicated terminals (kVA)	6.0×1 / 6.6×1
- Outlets (kVA)	1.5×4 / 1.65×4
Power factor (%)	3-phase 80 (lagging) / Single-phase 100

ENGINE	
Make, Model	KUBOTA V2403-K3A
Type	Swirl chamber
Rated output (kW)	19.1 / 23.7
Rated output (PS)	26 / 32.2
Rated speed (min-1)	1,500 / 1,800
Fuel tank capacity (L)	70
Engine oil amount (L)	9.5
Battery × quantity	80D26R×1
DIMENSION & WEIGHT, etc	
L×W×H (mm)	1,550×700×980
Dry weight (kg)	610
Operating weight (kg)	680
Sound power level in decibels (dB)	86 / 90
Sound pressure level (dB[A])	59 / 63
Designated emissions regulation	JPN Stage 3

