

# GENERATOR

## SDG45SE-3B2

BRAND	AIRMAN
MODEL	SDG45SE-3B2
<b>GENERATOR</b>	
Type	Single Voltage
Frequency (Hz)	50 / 60
<b>3-phase 4 wires</b>	
- Prime Output (kVA)	37 / 45
- Stanby Output (kVA)	37 / 45
- Voltage (V)	400/440
- Current (A)	53.4 / 59
<b>Single-phase auxiliary output</b>	
- Voltage (V)	-
- Dedicated terminals (kVA)	-
- Outlets (kVA)	-
Power factor (%)	3-phase 80 (lagging) / Single-phase 100

<b>ENGINE</b>	
Make, Model	KUBOTA V3600-T-K3A
Type	swirl chamber, Turbo-Charged
Rated output (kW)	35 / 42.5
Rated output (PS)	47.6 / 57.8
Rated speed (min-1)	1,500 / 1,800
Fuel tank capacity (L)	100
Engine oil amount (L)	13.2
Battery × quantity	80D26R×1
<b>DIMENSION &amp; WEIGHT, etc</b>	
L×W×H (mm)	1,870×860×1,220
Dry weight (kg)	910
Operating weight (kg)	1020
Sound power level in decibels (dB)	86 / 88
Sound pressure level (dB[A])	58 / 61
Designated emissions regulation	JPN Stage 3

