

# GENERATOR

## SDG60S-3A6

BRAND	AIRMAN
MODEL	SDG60S-3A6
<b>GENERATOR</b>	
Type	Dual Voltage
Frequency (Hz)	50 / 60
<b>3-phase 4 wires</b>	
- Prime Output (kVA)	50 / 60
- Stanby Output (kVA)	55 / 66
- Voltage (V)	200/400 / 220/440
- Current (A)	144/72.2 / 157/78.7
<b>Single-phase auxiliary output</b>	
- Voltage (V)	100 / 110
- Dedicated terminals (kVA)	7.5x2 / 8.25x2
- Outlets (kVA)	1.5x4 / 1.65x4
Power factor (%)	3-phase 80 (lagging) / Single-phase 100

<b>ENGINE</b>	
Make, Model	ISUZU BB-4BG1T
Type	Direct-Injection, Turbo-Charged
Rated output (kW)	48.1 / 57.4
Rated output (PS)	65.4 / 78
Rated speed (min-1)	1,500 / 1,800
Fuel tank capacity (L)	135
Engine oil amount (L)	14
Battery x quantity	80D26Rx1
<b>DIMENSION &amp; WEIGHT, etc</b>	
LxWxH (mm)	2,090x860x1,220
Dry weight (kg)	1,120
Operating weight (kg)	1,260
Sound power level in decibels (dB)	86 / 90
Sound pressure level (dB[A])	59 / 63
Designated emissions regulation	JPN Stage 2

